

Universal Loop Through and Individual Sockets

- Easy mounting with screws or clamps for flush-and surface mounting.
- Zinc plated alloy housing for excellent corrosion protection and grounding.
- High selectivity and low loss TV/Satellite separating filter.
- Outputs : Socket for RF, plug for TV both to IEC 60169-2, F-socket for satellite.
- Connecting system for inner conductor 0.8-1.3 mm and outer conductor up to 5.5mm.
- With DC passage through SAT output.
- The sockets are suitable for all flush mounting boxes (58 mm).
- The cover plate is part of the scope of supply.

- با قابلیت نصب آسان از طریق پیچها و چنگکها در کلیه حالات توکار و روکار.
- بدنه دایکاست دارای پوشش روی جهت جلوگیری از خوردگی و اتصال زمین مناسب.
- دارای فیلتر جداکننده TV/SAT با افت کم و منحنی عبور مناسب برای هر باند.
- شامل اتصال F جهت خروجی SAT و اتصال IEC جهت خروجی TV و Rd.
- قطر داخلی اتصالات با احتساب مغزی فیش 0.8-1.3mm و قطر بیرونی آن تا 5.5mm می باشد.
- با قابلیت عبور ولتاژ DC در خروجی SAT و خروجی عبوری FO314.
- قابل نصب در تمام قوطی های توکار پرز طبق استاندارد (58mm).
- درب پوش پرز در بسته بندی محصول می باشد.




SMATV Antenna Outlets

5-2150 MHz

SAT / TV / Radio **پریزهای آنتن مرکزی ۳ خروجی**

- Individual outlets are used to end cables coming from the tap-off (multi-tap), multiswitch or sat LNB (star structure).
- Through pass outlets can also be cascaded (tree structure). The last outlet on a trunk or stub cable must be fitted with a terminator resistor.



Cover Plate



Mounting Fram

Model			FO33			FO314		
Frequency range	MHz		FM dB	TV dB	SAT dB	FM dB	TV dB	SAT dB
Thru.loss	5-40	AM					1	
	47-68	VHFI					1	
	87.5-108	FM					1	
	174-470	VHFIII		—			1	
	470-862	UHF					1	
	950-2150	SAT					2-3	
Side loss	5-40	AM	2	1.5	—	14	14	—
	47-68	VHFI	2	1.5	—	14	14	—
	87.5-108	FM	2	1.5	—	14	14	—
	174-470	VHFIII	—	1.5	—	—	14	—
	470-862	UHF	—	1.5	—	—	14	—
	950-2150	SAT	—	—	2-3	—	—	14

Remot Feed Voltage / Current

max. 24V/500mA via SAT & Thru.out