

The Handy Level Meters for Quick and Optimum Alignment of Antennas

Mini Handy TV Signal Level Meter

DS2002 / DS2003

Introduction :

DS2002/2003 is a handset, smaller, lighter, more practical and more convenient to use. The streamlined appearance design makes it look smarter. DS2003 add more function: larger frequency range (46MHz~1GHz), Digital Channel Power, 4 channel tilt and so on

Key Features :

- More dependable : made of high strength material; passed the various shock and bump tests .
- Smarter design : high technique integrated design ; lighter weight make you enjoy your working .
- Level, Tilt test

معرفی :

از دستگاه اندازه گیری DS2002 / 2003 با توجه به ابعاد و وزن کم و قابل استفاده بودن بصورت دستی ، در عملیات نصب می توان براحتی بهره برد . بواسطه طراحی خاص در ظاهر بسیار زیبا می باشد . دستگاه DS2003 دارای ویژگی های : محدوده فرکانسی بازر (46MHz~1GHz) ، اندازه گیری قدرت کانالهای دیجیتال و امکان اندازه گیری همزمان 4 کانال تلویزیونی و اختلاف آنها را نیز دارا می باشد .

ویژگی های اصلی :

- کاملاً قابل اطمینان : به لحاظ استفاده از مواد با استحکام بالا و انجام انواع تست های ضربه و برخورد .
- طراحی زیبا : بواسطه بکارگیری مهارت بالا در یکپارچه سازی و سبک بودن ، کار با آن را برای شما لذت بخش می کند .
- اندازه گیری سطح و اختلاف کانالهای تلویزیونی .

Model	DS1001	DS2002	DS2003
Frequency			
Range	46MHz~864MHz		46MHz~1GHz
Accuracy	± 50ppm		
Frequency Step	50 kHz, 100kHz, 1MHz, 10MHz and 100MHz		
Tuning Resolution	50 kHz		
Level Measurement			
Range	30dBμV~120dBμV		
Accuracy	± 2dB @ 25°C	± 2dB (20°C±5°C)	
Resolution	0.5 dB		
Digital Power Range	—	40dBμV~110dBμV	
Voltage			
Input Range	1 V~100V (AC/DC)		—
Measured Accuracy	± 2V		—
Resolution	1V		—
Others			
Dimension	168mmx130mmx65mm	About 168mm x 71mmx42mm	
Weight	About 600g	About 368g (Including the battery)	
Working Temperature	-10°C to 40°C		
Audio	Built-in Speaker	Built-in Speaker (Auto on in SINGLE FREQ. mode)	—
Power Supply	7.2V/1.4AH Ni-MH	3.6V/2.1AH Ni-MH	3.6V/2.5AH Ni-MH
Operating Time	≥ 6 hours	≥ 6hours (Shut off the audio and LCD backlight)	≥ 4 hours
Charging Time	Round 12 hours (Power off the meter)		

DS2002 / 2003

